

# SYNCHRONOUS INFORMATION REPRODUCTION APPARATUS

## BACKGROUND OF THE INVENTION

The present invention relates to a synchronous information reproduction apparatus, a synchronous information reproduction method and a storage medium storing therein a synchronous information reproduction program for synchronizing and reproducing multimedia information such as music performance information, polygon CG animation data, movie data and musical tone waveform sample data.

There is known a method of synchronizing and reproducing multimedia information such as musical tones, images and voices. For example, in parallel to reproduction of music performance information such as MIDI information, various kinds of multimedia information such as image information like CG (computer graphics) images, movie images, sound, and musical tone waveform information are reproduced.

However, in a conventional apparatus for reproducing multimedia information in association with music performance information, there is a problem that synchronism between the music performance information and the image information or the like is lost when a tempo of the music performance information is changed during the course of the reproduction.

Thus, in order to eliminate such a disadvantage, there is proposed a synchronous information reproduction method capable of synchronously reproducing a video even if a tempo of a musical tone which is automatically reproduced is

changed during the course of the reproduction (Japanese Patent Application Laid-open No. 333673/1998). This method prepares a synchronization information table, in which location information indicative of a series of song points, music tempo information and a time at which these sets of information are updated are associated with each other. This conventional method can reproduce a video synchronized with a change in tempo of a song by making a reference to the table. As a result, even if a tempo of the song is changed along the way, the video can be reproduced without losing the synchronization. However, the synchronization information table must be prepared and this table needs to be sequentially restructured in this method. Thus, the synchronization processing and creation of the reproduction content are troublesome.

Further, another conventional apparatus which associates musical information with image information and the like for reproduction reproduces the musical information and the image information by a single player device, but does not reproduce the musical information and the associated image information by using a multiple of player devices connected through a network and the like.

Furthermore, in order to reproduce the musical information and the image information, a time difference after starting reproduction process or commanding reading of each information till an actual output is not taken into consideration, and hence there is no guarantee that each

information is reproduced with desired timing.

Moreover, there is a demand for reproducing not only the image information but also other multimedia information such as musical tone, e.g., WAVE data or sound waveform sample data in association with the MIDI performance information.

#### SUMMARY OF THE INVENTION

Therefore, it is an object of the present invention to provide a synchronous information reproduction apparatus, a synchronous information reproduction method and a storage medium storing therein a synchronous information reproduction program capable of synchronously reproducing multimedia information with reduced processing burdens.

Further, it is another object of the present invention to provide a synchronous information reproduction apparatus, a synchronous information reproduction method and a storage medium storing therein a synchronous information reproduction program, capable of absorbing differences in the processing delay time of respective multimedia information, capable of completely synchronously reproducing the multimedia information.

Furthermore, it is still another object of the present invention to provide a synchronous information reproduction apparatus, a synchronous information reproduction method and a storage medium storing therein a synchronous information reproduction program, by which the

processing cannot be interrupted when out of synchronism occurs.

To achieve this aim, according to one aspect of the present invention, there is provided a synchronous information reproduction apparatus comprising: a receiving section for receiving a clock signal; a storing section for storing object information; reproduction point generating section for generating information indicative of a reproduction point of the object information stored in the storing section; a reproducing section for reading and reproducing the object information from the storing section based on the reproduction point generated by the reproduction point generating section; a synchronizing section for synchronizing an incremental speed of the reproduction point generated by the reproduction point generating section with a reception timing of the clock signal based on a reception time interval of the clock signal; and an outputting section for outputting a content of the object information reproduced by the reproducing section.

Further, according to another aspect of the present invention, there is provided a synchronous information reproduction apparatus comprising: a receiving section for receiving a clock signal; a storing section for storing object information; a reproduction point generating section for generating information indicative of a reproduction point of the object information stored in the storing section; a reproducing section for reading and reproducing the object

information from the storing section based on the reproduction point generated by the reproduction point generating section; a synchronizing section for synchronizing an incremental speed of the reproduction point generated by the reproduction point generating section with a reception timing of the clock signal based on a reception time interval of the clock signal; an outputting section for outputting a content of the object information reproduced by the reproducing section; and a reproduction point correcting section for measuring a time duration from start of reproduction process of the object information by the reproducing section till actual output of the object information from the outputting section and correcting the reproduction point in accordance with the measured time duration.

Furthermore, when a command by a user or an out of synchronism between the clock signal and the object information is detected or when stop of supply of the clock signal is detected, the operation of the synchronizing section is stopped, and the reproduction point is generated at a predetermined incremental speed in the reproduction point generating section.

Moreover, selection of the object information stored in the storing section and control of the reproduction process by the reproducing section are carried out in accordance with an externally supplied signal.

In addition, the object information is divided into

blocks in accordance with the clock signal interval.

Additionally, according to still another aspect of the present invention, there is provided a synchronous information reproduction apparatus comprising: a storing section for storing a plurality of sets of object information; a reproduction point generating section for generating information indicative of respective reproduction points of a plurality of the sets of object information stored in the storing section; a reproducing section for reading and reproducing the plurality of the sets of object information from the storing section based on the reproduction points generated by the reproduction point generating section; an outputting section for outputting contents of the object information reproduced by the reproducing section; and a reproduction point correcting section for measuring, for each set of object information, a time duration from start of reproduction process of the object information by the reproducing section till actual output of the object information from the outputting section and correcting each reproduction point in accordance with the measured time duration.

Further, according to one aspect of the present invention, there is provided a synchronous information reproduction method for reproducing one or a plurality of sets of object information stored in a storing section in synchronization with a clock signal, comprising: a reception step of receiving the clock signal; a generation step of

generating location information indicative of a reproduction point of the object information; a reproduction step of reading and reproducing the object information from the storing section based on the reproduction point generated by the generation step; a synchronization step of synchronizing an incremental speed of the reproduction point generated by the generation step with a reception timing of the clock signal based on a reception time interval of the clock signal; and an output step of outputting a content of the object information reproduced by the reproduction step.

Furthermore, according to another aspect of the present invention, there is provided a synchronous information reproduction method for reproducing one or a plurality of sets of object information stored in a storing section in synchronization with a clock signal, comprising: a reception step of receiving the clock signal; a generation step of generating location information indicative of a reproduction point of the object information; a reproduction step of reading and reproducing the object information from the storing section based on the reproduction point generated by the generation step; a synchronization step of synchronizing an incremental speed of the reproduction point generated by the generation step with a reception timing of the clock signal based on a reception time interval of the clock signal; an output step of outputting a content of the object information reproduced by the reproduction step; and a reproduction point correction step of measuring a time

duration from start of processing in the reproduction step till actual output of the object information and correcting the reproduction point in accordance with the measured time duration.

Moreover, when a command by a user or an out of synchronism between the clock signal and the object information is detected or when stop of supply of the clock signal is detected, the operation of the synchronization step is stopped, and the reproduction point is generated at a predetermined incremental speed in the reproduction step.

In addition, according to still another aspect of the present invention, there is provided a synchronous information reproduction method for reproducing a plurality of sets of object information stored in a storing section, comprising: a generation step of generating information indicative of respective reproduction points of the plurality of the sets of object information stored in the storing section; a reproduction step of reading and reproducing the plurality of the sets of object information from the storing section based on the reproduction points generated by the generation step; an output step of outputting contents of the object information reproduced by the reproduction step; and a reproduction point correction step of measuring, for each object information, a time duration from start of processing in the reproduction step till actual output of the object information and correcting each reproduction point in accordance with the measured time duration.



Additionally, according to the present invention, there is provided a storage medium for storing therein a program for causing a computer to reproduce one or a plurality of sets of object information stored in a storing section in synchronization with a clock signal, the program comprising: a reception step of receiving the clock signal; a generation step of generating information indicative of a reproduction point of the object information; a reproduction step of reading and reproducing the object information from the storing section based on the reproduction point generated by the generation step; a synchronization step of synchronizing an incremental speed of the reproduction point generated by the generation step with a reception timing of the clock signal based on a reception time interval of the clock signal; and an output step of outputting a content of the object information reproduced in the reproduction step.

Further, according to another aspect of the present invention, there is provided a storage medium for storing therein a program for causing a computer to reproduce one or a plurality of sets of object information stored in a storing section in synchronization with a clock signal, the program comprising: a reception step of receiving the clock signal; a generation step of generating information indicative of a reproduction point of the object information; a reproduction step of reading and reproducing the object information from the storing section based on the reproduction point generated by the generation step; a synchronization step of

synchronizing an incremental speed of the reproduction point generated by the generation step with a reception timing of the clock signal based on a reception time interval of the clock signal; an output step of outputting a content of the object information reproduced in the reproduction step; and a reproduction point correction step of measuring a time duration from start of processing in the reproduction step till actual output of the object information and correcting the reproduction point in accordance with the measured time duration.

Furthermore, the program further comprises a step of stopping the operation of the synchronization step and generating the reproduction point at a predetermined incremental speed in the reproduction step when a command by a user or an out of synchronism between the clock signal and the object information is detected or when stop of supply of the clock signal is detected.

Moreover, according to still another aspect of the present invention, there is provided a storage medium for storing therein a program for causing a computer to reproduce a plurality of sets of object information stored in a storing section in synchronization with a clock signal, the program comprising: a generation step of generating information indicative of respective reproduction points of the plurality of the sets of object information; a reproduction step of reading and reproducing the plurality of the sets of object information from the storing section based on the

reproduction points generated by the generation step; an output step of outputting contents of the object information reproduced in the reproduction step; and a reproduction point correction step of measuring, for each set of the object information, a time duration from start of processing in the reproduction step till actual output of the object information and correcting each of the reproduction points in accordance with the measured time duration.

#### BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a functional block diagram showing a structure of a synchronous information reproduction apparatus to which a synchronous information reproduction method according to the present invention is applied.

FIG. 2 is a view showing the structure of one embodiment of the synchronous information reproduction apparatus to which the synchronous information reproduction method according to the present invention is applied.

FIG. 3 is views for explaining each song file stored in a main body of the apparatus and an external MIDI equipment, in which FIG. 3(a) is a view showing an example of a song file, FIG. 3(b) is a view showing an example of the data structure of reproduction data, and FIG. 3(c) is a view showing another example of the data structure of reproduction data.

FIG. 4 is a view showing the state of synchronous reproduction when a cycle of a timing clock is extended

during the course of performance in the synchronous information reproduction apparatus according to the present invention.

FIG. 5 is a view showing the state of synchronous reproduction when a cycle of the timing clock is shortened during the course of performance in the synchronous information reproduction apparatus.

FIG. 6 is a flowchart for illustrating the overall operation of the main body of the inventive apparatus.

FIG. 7 is a flowchart of MIDI monitoring timer interruption processing.

FIG. 8 is a flowchart of reproduction timer interruption processing for realizing a synchronous operation mode 1.

FIG. 9 is a flowchart showing a modification of the reproduction timer interruption processing for realizing the synchronous operation mode 1.

FIG. 10 is a flowchart of the reproduction timer interruption processing for realizing a synchronous operation mode 2.

FIG. 11 is an operation flowchart of the external midi equipment.

#### DETAILED DESCRIPTION OF THE INVENTION

FIG. 1 is a functional block diagram showing a structure of a synchronous information reproduction apparatus to which a synchronous information reproduction method

according to the present invention is applied. In the drawing, a portion 1 surrounded by a broken line denotes a synchronous information reproduction apparatus for carrying out reproduction of object information, and 2 designates an external clock device for supplying a clock signal for synchronizing reproduction of the object information to the synchronous information reproduction apparatus 1.

In case of reproducing object information in synchronization with performance of a song, the object information including image information of, e.g., a still picture or a moving picture, CG animation image information indicative of the progression state of performance of the song, musical tone waveform information and voice information, a clock signal whose cycle corresponds to a performance tempo of the song is supplied from the external clock device 2, and the synchronous information reproduction apparatus 1 reproduces and outputs the object information in the form of the above-described various kinds of contents in synchronization with the clock signal. Here, even if the cycle of the clock signal supplied from the external clock device 2 is changed during reproduction of the object information due to a change in the performance tempo of the song, it is possible to following that change in cycle of the clock signal in the synchronous information reproduction apparatus 1 so that the object information can be reproduced and outputted without losing synchronization.

As a clock signal based on the music performance

information of the song supplied from the external clock device 2, a timing clock (F8) of, e.g., a MIDI message can be used. Further, in such a case, as the external clock device 2, an external MIDI equipment such as a sequencer or a clock master can be used, and music performance information (MIDI data) of that song can be supplied to the synchronous information reproduction apparatus 1 together with the clock signal. Furthermore, both of the music performance information of that song and the object information can be reproduced and outputted in the synchronous information reproduction apparatus 1. Moreover, a plurality of the synchronous information reproduction apparatuses 1 can be connected to a single external clock device 2 in parallel, and a plurality of the synchronous information reproduction apparatuses 1 can be used to reproduce the object information on a plurality of mediums such as image, text, voice, sound and so on. In addition, reproduction and output of the music performance information may be performed by the external clock device and reproduction and output of the object information may be carried out by one or a plurality of synchronous information reproduction apparatuses 1.

Here, description will be given on the assumption that the control information (for example, a MIDI message) including information for designating start/end of the performance or information for selecting a song to be performed is supplied from the external clock device 2 to the synchronous information reproduction apparatus 1 together

with the clock signal (for example, F8 of the MIDI message).

In the synchronous information reproduction apparatus 1, a reference numeral 11 denotes receiving section for receiving a clock signal and a control signal from the external clock device 2; 12, a mode switching section for setting a synchronous mode (an external synchronous mode or an internal synchronous mode) in the synchronous information reproduction apparatus 1; 13, a synchronizing section for setting a reproduction speed of object information stored in the storing section 16 in accordance with a reception timing of the clock signal from the receiving section 11; 14, reproduction point generating section for generating a reading position (reproduction point) of object information stored in the storing section 16 sequentially in accordance with the reproduction speed determined by the synchronizing section 13; 15, a reproducing section for reading the object information stored in the storing section 16, performing interpolation according to needs and thereafter generating a corresponding reproduction output signal; 17, an outputting section for outputting the object information in accordance with the reproduction output signal from the reproducing section 15; 18, a reproduction point correcting section for measuring a time duration from start of reproduction process by the reproducing section 15 till completion of the reproduction output in the outputting section 17 so as to correct the reproduction point from the reproduction point generating section 14; and 19, an internal clock section for

generating an internal clock signal for specifying an operation timing of each of the constituent sections in the synchronous information reproduction apparatus 1.

As described above, although this synchronous information reproduction apparatus 1 has an external synchronous mode for reproducing the object information in synchronization with a clock signal fed from the external clock device 2, and an internal synchronous mode for reproducing the object information at a preset reproduction speed irrespective of the clock signal. Here, it is assumed that the external synchronous mode is set by the mode switching section 12. Incidentally, when a command by a user or collapse of the external synchronization is detected or failure in supply of the clock signal due to disconnection and the like is detected, the mode switching section 12 sets the operation mode to the internal synchronous mode so that the object information can be reproduced at the preset reproduction speed or the last reproduction speed before collapse of the synchronization.

In addition, object information which is reproduced in association with a song in accordance with a tempo of the song to be performed is stored in the storing section 16 as a sequence of data (reproduction data). For example, object information on various kinds of mediums such as polygon CG operation data (for example, sequence of data of joint angles of a skeleton model), MIDI performance data, movies, or WAVE data is stored as the sequence of data.



In the synchronous information reproduction apparatus 1 having such an arrangement, the clock signal and the control information (MIDI message) from the external clock device 2 are received by the receiving section 11 of the synchronous information reproduction apparatus 1; location information indicative of a reception timing of the received clock signal is supplied to the synchronizing section 13; control information indicative of start/stop of performance in the above-mentioned control information is supplied to the reproduction point generating section 14; and information for selecting a song to be performed in the above-mentioned control information is supplied to the storing section 16.

The synchronizing section 13 determines a reproduction speed of the object information stored in the storing section 16 based on the information indicative of the reception timing of the clock signal fed from the receiving section 11. That is, the synchronizing section 13 predicts a time until the next clock signal is received from a reception interval of the past clock signals, and calculates a speed for reading the object information to be reproduced until the next clock signal is received based on the prediction (an updating quantity, i.e., an increment amount of a reading address of reproduction data stored in the storing section 16). As a result, even if an incoming cycle of a variable clock signal is changed, reading of the reproduction data can be synchronized with the variable clock signal.

This reproduction speed information is supplied to the reproduction point generating section 14, and the reading address (reproduction point) of the reproduction data to be read from the storing section 16 is calculated in the reproduction point generating section 14 so that the reading address is supplied to the reproducing section 15.

The processing for generating the reproduction point by the reproduction point generating section 14 is executed in a cycle according to a type of the object information. For example, if the reproduction data is WAVE data, the reproduction point is updated in accordance with each cycle corresponding to the sampling frequency (for example, 44.1 kHz) of WAVE data. In case of CG data or movie data, the reproduction point is updated in accordance with a cycle determined according to a number of reproduction frames per one second (for example, 30 frames/second).

The reproducing section 15 reads corresponding reproduction data from the storing section 16 based on the reproduction point supplied from the reproduction point generating section 14, and generates the reproduction output signal according to the reproduction data so that the generated signal can be supplied to the outputting section 17. Usually, the interpolation processing in the order of a decimal fraction is carried out according to needs, since the reproduction point includes a decimal value. Specifically, this reproducing section 15 has means for reading the reproduction data from the storing section 16 and means for

executing the interpolation processing according to needs. Further, if the object information is a CG animation image, the reproducing section 15 has a graphic engine or a decoder. If the object information is musical tone waveform sample data such as WAVE data, the reproducing section has a D/A converter.

The reproduction output signal outputted from the reproducing section 15 is supplied to the outputting section 17, and corresponding object is outputted. If the object information is image data, this outputting section 17 has a display unit. If the object information is musical tone waveform sample data, the outputting section 17 has a sound system.

Here, depending on types of object information, a time duration from start of the reproduction process by the reproducing section 15 till output of the object information to the outputting section 17 may differ. For example, in case of reproduction of a CG animation image, a three-dimensional coordinate calculation about an apex and a normal line of each object, light illumination and coloring, a texture coordinate calculation, polygon formation, a projection coordinate calculation, visual field clipping, bit map creation, and rendering processing (image generation processing) such as hidden surface/transmission processing are carried out based on scene information or operation data. On the other hand, in case of reproduction of musical tone waveform data, only the interpolation processing of the read

musical tone waveform sample data can suffice. Furthermore, the time duration required for processing may differ depending on hardware used in the reproducing section 15. Therefore, the reproduction point correcting section 18 measures a time duration from start of the reproduction process by the reproducing section or from a command of reproduction to the reproducing section 15 till actual output of the object information to the outputting section 17, and shifts the reproduction point outputted from the reproduction point generating section 14 rearwards by a quantity corresponding to the measured time duration. Moreover, the obtained reproduction point is supplied to the reproducing section 15, and a deviation of the output timing caused due to a difference in contents type such as a sound or CG or in hardware used as the reproducing section is compensated so that the information of different types of mediums can be completely synchronously outputted with each other.

As described above, according to the synchronous information reproduction apparatus of the present invention, the cycle of the clock signal received in the synchronizing section 13 is measured, and a reception time of a next clock signal is predicted based on the measured cycle in order to determine a reading speed of the object information. Therefore, even if the cycle of the clock signal supplied from an external clock device is changed, the object information can be reproduced and outputted in synchronization with the clock signal.

Additionally, since the reproduction point correcting section 18 corrects the reproduction point so as to absorb a difference in processing time until the object information is outputted, the out of synchronization caused due to a difference in medium or a difference in hardware can be completely eliminated

Embodiments of the synchronous information reproduction apparatus and the synchronous information reproduction method according to the present invention will now be described in detail hereinafter.

FIG. 2 is a view showing the structure of one embodiment of the synchronous information reproduction apparatus to which the synchronous information reproduction method according to the present invention is applied. In this drawing, reference numeral 1 denotes a main body corresponding to the above-described synchronous information reproduction apparatus, and it is assumed that a personal computer is used as the main body in this embodiment. In addition, reference numeral 2 designates the above-mentioned external clock device, and it is assumed that the external clock device is an external MIDI equipment such as a sequencer or a MIDI keyboard. Further, it is determined that the external MIDI equipment 2 functions as a master while the main body 1 serves as a slave. Selection of a song to be performed and control for start and end of reproduction of that song are carried out in the external MIDI equipment 2, and music performance information (MIDI data) of that song is

supplied to the main body 1. Furthermore, synchronous reproduction process of object information such as CG of the performance operation and reproduction process of the received music performance information are executed in the main body 1.

In the main body 1, reference numeral 21 denotes a CPU for carrying out control of the main body 1; 22, a ROM storing therein a control program or various kinds of parameters; 23, a RAM used as a work area in which a program is loaded; 24, a clock generator for generating an operation clock or various kinds of timer interruptions; 25, a MIDI interface circuit (MIDI I/F) for transmitting/receiving MIDI data to/from the external MIDI equipment 2 and the like; 26, an input operator such as a character keyboard or a mouse; 27, an external storage device such as a hard disk device or a CD-ROM drive device; 28, a sound source for reproducing a musical tone waveform signal from MIDI data; 29, a sound system for D/A converting and amplifying a musical tone waveform signal from the sound source 28; 30, an image computation unit (graphic engine) for generating an image signal from CG image data indicative of a performance operation and the like or movie data; and 31, a display unit for displaying the CG image, the movie from the image computation unit 30 or various kinds of messages.

Further, in the external MIDI equipment 2, reference numeral 41 designates a CPU for controlling the entire operation of the external MIDI equipment 2; 42, a ROM for

storing therein a control program and various kinds of parameters; 43, a RAM used as a work area and the like; 44, a clock generator for generating an operation clock and various kinds of timer interruptions; 45, a MIDI interface circuit (MIDI I/F) for inputting/outputting MIDI data with respect to the main body 1; 46, an input operator such as a MID keyboard, an operation panel and a wheel; 47, an external storage device such as a hard disk device; 48, a sound source for reproducing a musical tone waveform signal from MIDI data; 49, a sound system for D/A converting and amplifying a musical tone waveform signal from the sound source 48 to be outputted; and 50, a display unit for displaying various kinds of messages and the like.

Here, the external storage device 47 or the RAM 43 in the external MIDI equipment 2 stores therein music performance data (MIDI data, SMF (Standard MIDI File)) in accordance with each song to be performed, and the music performance data (MIDI data) of a selected song is supplied to the main body 1 through the MIDI interface 45.

The external storage device 27 or the RAM 23 in the main body 1 stores therein object information which is reproduced in association with the music performance in accordance with each song. In the above-described external synchronous mode, object information of a song to be selected by a MIDI message from the external MIDI equipment 2 is read and reproduced in synchronization with a timing clock (F8) included in the MIDI message.

The respective external storage devices 27 and 47 in the main body 1 and the external MIDI equipment 2 accommodate therein song files storing therein information concerning music performance in accordance with each song. Description will now be given as to the song files with reference to FIG. 3.

FIG. 3(a) is a table showing an example of a song file accommodated in each of the main body 1 and the external MIDI equipment 2. As shown in the drawing, in the song file of the external MIDI equipment 2, performance data is recorded in accordance with each song. The performance data is stored in the form of an SMF (Standard MIDI file) as described above. In the illustrative example, respective sets of performance data for songs 1 to 3 are stored.

Moreover, the song file stored in the main body 1 stores object information of various kinds of mediums such as music performance data, CG operation data, WAVE data and movie data which should be reproduced in association with music performance in accordance with each song. One or a plurality of sets of object information are prepared in accordance with the song to be performed. For example, in case of one song, only predetermined operation data for animating CG polygons is recorded as object information. In case of another song, both the similar operation data and the MIDI performance data are recorded. In the illustrative example, with respect to a song 1, the CG operation data is stored together with the performance data for the song 1 as



the object information. The performance data and the movie data are stored for a song 2 as the object information, and the CG operation data, the WAVE data and the movie data are stored for a song 3 as the object information.

FIG. 3(b) is a diagram showing an example of a data structure of the object information stored in the main body 1. In the illustrative example, each set of object information is constituted by a header portion storing therein information of entire data and reproduction data consisting of a plurality of sets of packet data obtained by dividing the sequence of data into a plurality of blocks (which will be referred to as packets hereinafter) in matching with the clock timing. That is, in each packet, the reproduction data which should be reproduced after reception of the timing clock (F8) till reception of a next timing clock is arranged in time series.

Here, the reproduction data is divided into packets at intervals of the timing clocks (F8) and stored. Therefore, at the time of reproduction, a number of timing clocks (F8) received after start of reproduction equals to a packet number which is currently reproduced. Accordingly, comparing a number of received timing clocks (F8) with the packet number which is currently reproduced enables detection of the lost of synchronization of the reproduction data.

Supplementary information inherent to the object information such as a size of the entire object information or a number of packets is stored in the header portion of the

object information. Taking the case where the object information is CG animation information for instance, there is stored information such as a data size, an object property (data such as a shape, an arrangement or a skeleton model of a polygon object, or a pointer indicative of an area in which data is stored), a number of packets, and reproduction speed information (default reproduction speed).

Here, the supplementary information (for example, the object property) may be stored in an additional file so that reference can be made to this file.

In addition, as shown in the drawing, the packet data is constituted by a header portion of each packet and time series data, and the header portion of the packet includes information indicative of, e.g., a packet size (or an address at the end of the packet) and a number of samples in the packet.

Incidentally, although the reproduction data is physically divided into packets in accordance with incoming intervals of the timing clocks in the example shown in FIG. 3(b), the reproduction data does not have to be physically divided into packets in this way. That is, as shown in FIG. 3(c), packet address information such as an address of reproduction data (address with a head position as a reference) according to timing clock reception timing may be enumerated in the header portion of the object information as a part of the header information so that the object information can be logically divided into packets at the

timing of reading. That is, as shown in the drawing, in the header portion are stored an initialization information portion recording therein information similar to that in the header portion of the object information and packet address information indicative of an address of, sequence of data according to reception timing of each timing clock. It is to be noted that E denotes a code indicative of an end of the header.

Incidentally, when the object information is CG animation data indicative of the progressive state of music performance of the song, such animated reproduction data as that changes in a joint angle of the skeleton model of a performer with time are aligned in time series. In addition, in case of WAVE data or movie data, data recorded in a sampling cycle according to a type of data is provided.

Further, although the object information includes the performance data as described above, data having such a format as shown in FIGs. 3(a) and (b) does not have to be used as the performance data of MIDI. That is, since the MIDI data is synchronized with the timing clock (F8) from the external clock device 2, the usual MIDI file can be used as it stands.

Furthermore, although different files are used in accordance with each set of object information in the above description, a plurality of sets of reproduction data of different mediums or the same medium such as the graphic operation data (data indicative of an operation track of each

part in a body of a performer or each part in an instrument in the CG animation) and the MIDI data may be stored in one file. Alternatively, they may be stored in different files and index data for making reference to a corresponding file may be prepared.

Description will now be given as to the state of synchronous reproduction in the synchronous information reproduction apparatus according to the present invention having such a structure.

As described above, in this embodiment, the external MIDI equipment 2 serves as a master to select a song to be performed or the control reproduction of the selected song and supplies music performance information of the selected song to the main body 1. Thus, the detail of MIDI messages supplied from the external MIDI equipment 2 and the outline of the processing in the main body 1 according to these messages will be first described. As is well known, the MIDI messages are roughly classified into channel messages (80 to EF) concerning the actual performance, and system messages (F0 to FF) commonly used in the entire MIDI system. The system messages are further divided into a common message, a real time message and an exclusive message. The external MIDI equipment 2 transmits selection information of a song to be performed, control information for controlling the reproduction operation, and a synchronous signal for reproducing the object information in synchronization with the performance of the song to the main body 1 by using the

system message.

Upon starting the operation, the external MIDI equipment 2 transmits ACTIVE SENSING (FE) to the main body 1. As a result, the main body 1 can confirm that the external MIDI equipment 2 is connected. Furthermore, when a song to be performed is selected by the operation panel of the input operator 46 in the external MIDI equipment 2, a song number (ID) for designating the selected song is transmitted to the main body 1 by the SONG SELECT (F3). Consequently, the main body 1 loads the object information of the selected song. Moreover, when an FF (fast-forward) or REW (rewind) button is operated on the operation panel in the external MIDI equipment 2, the song position pointer (F2) is transmitted to the main body 1 in accordance with this operation, and a reproduction start position of the object information is set in accordance with this pointer. In addition, when start of performance is directed in the external MIDI equipment 2, START (FA) is transmitted, and the timing clock (F8) and a MIDI message such as channel messages (80 to EF) are also transmitted. In accordance with this transmission, the main body 1 starts to count the timing clock (F8), and also commences reproduction of the object information in synchronization with this counting. Additionally, the main body 1 transmits the channel message to the sound source 28 to start reproduction of the music performance information. Further, when the processing for stopping the performance is carried out on the operation panel in the external MIDI

equipment 2, STOP (FC) is transmitted to the main body 1, and the main body 1 stops the music performance and the reproduction operation. Furthermore, when the operation for commanding restart is performed on the operation panel of the external MIDI equipment 2, CONTINUE (FB) is transmitted to the main body 1, and the main body 1 restarts the reproduction operation of the music performance information and the object information from the stopping position.

Description will now be given as to the state of synchronous reproduction of the object information in the synchronous information reproduction apparatus according to the present invention.

FIGS. 4 and 5 are time charts showing the state of synchronous reproduction in the synchronous information reproduction apparatus according to the present invention having such an arrangement. FIG. 4 shows how the object information is reproduced while maintaining synchronization with the timing clock when the cycle of the timing clock (F8) is extended during the music performance, and FIG. 5 shows the same when the cycle of the timing clock is shortened. In these drawings, a horizontal axis represents a time axis; (a), a time; (b), reception timing of the timing clock (F8); (c), predicted reception timing of the timing clock; and (d) and (e), a packet of the reproduction data reproduced with each timing. The part (d) shows the state of reproduction in a first synchronous operation mode, and the part (e) shows the state of reproduction in a second synchronous operation mode.

As described above, there are two synchronous operation modes, i.e., the first synchronous operation mode and the second synchronous operation mode in the present invention.

In FIGs. 4 and 5, before the time  $t_1$ , it is assumed that connection between the main body 1 and the external MIDI equipment 2 is confirmed by at least the ACTIVE SENSING (FE), and selection of reproduction data is carried out by the SONG SELECT (F3) mentioned above. Furthermore, it is assumed that the timing clock (F8) is transmitted for initial synchronization before REPRODUCTION COMMAND (FA). Therefore, at the time  $t_1$ , a number of received clocks is set to 0 with a packet position at the top (packet number: 0).

When REPRODUCTION COMMAND (FA) is received at the time  $t_{FA}$ , the reproduction operation is then started at the time  $t_{start}$  at which the clock (F8) is received, and reading of the reproduction data is started from the packet 0.

Thereafter, the reading speed of the packet  $k$  is controlled based on intervals of the clocks (F8) measured immediately before. Moreover, in accordance with start of reading the packet  $k$ , a time  $t_{k+1}$  at which incoming of a next clock is predicted is specified.

(Synchronous Operation Mode 1)

If the next clock (F8) is not received (incoming cycle of the clock is extended) upon completion of reading of the packet  $k-1$ , as shown in the synchronous operation mode 1 in FIG. 4(d), data at the tail end of the packet  $k-1$  is repeatedly reproduced until the next clock arrives. Namely,

the reproduction operation is temporarily stopped until the next clock arrives. Then, when the clock arrives at the time  $t_k^{adj}$ , the reading speed is recalculated, and reproduction of the packet k is started at the calculated reproduction speed  $F_s$ .

On the other hand, as shown in FIG. 5, if the incoming cycle of the clock (F8) is shortened when reading the packet k-1, the next clock arrives before the time  $t_k$ .

In such a case, reproduction of the current packet k-1 is aborted when the clock arrives at the time  $t_k^{adj}$  (synchronous operation mode 1 in FIG. 5(d)).

Then, the reading speed is recalculated, and reproduction of the packet k is started at the calculated reading speed  $F_s$ .

As described above, according to the synchronous operation mode 1, synchronization established between reproduction of the reproduction data and the clock signal can be maintained in both cases where the reception cycle of the clock signal is extended and where the same is shortened. (Synchronous Operation Mode 2)

In the above-mentioned synchronous operation mode 1, it can be considered that reproduction is temporarily stopped when the clock cycle is extended, or the reproduction content becomes discontinuous when the clock cycle is shortened. As a countermeasure, in the synchronous operation mode 2, the synchronization processing is changed as follows.

If the next clock (F8) is not received (incoming



cycle of the clock is extended) upon completion of reading of the packet k-1 ( $t_k$ ), although the clock does not arrive at the time  $t_k$ , reading of the next packet k is started at the reproduction speed  $F_e$  used up to this time for the meanwhile ( $k_e$  in the drawing).

Then, when the clock arrives at the time  $t_k^{adj}$ , reproduction at the current speed is aborted, and reading speed of the packet data (the remaining part of the packet k: k') is recalculated based on the size of the remaining part of the packet k and the clock incoming interval ( $t_k^{adj} - t_{k-1}$ ). In addition, the reproduction is carried out at the recalculated speed  $F_m$ . Thereafter, the subsequent packet is reproduced at a reading speed  $F_s$  according to the timing clock (F8) having the extended cycle.

On the other hand, as shown in FIG. 5, if the incoming cycle of the clock (F8) is shortened during the reading of the packet k-1, the next clock arrives before reaching the time  $t_k$ .

In this case, as shown in FIG. 5(e), reproduction at the current speed  $F_s$  is aborted when the clock reaches the time  $t_k^{adj}$ , and the reading speed  $F_m$  of the packet data (remainder of the packet k-1 + packet k) is recalculated based on the size of the remainder of the packet k-1 + the packet k and the clock incoming interval ( $t_k^{adj} - t_{k-1}$ ). Further, the remainder of the packet k-1 + the packet k (= packet k') is reproduced at the recalculated reading speed  $F_m$ . Thereafter, reading of the packet is carried out at the

reading speed  $F_r$  according to the shortened cycle of the timing clock (F8).

Incidentally, in case of the synchronous operation mode 2, when the incoming cycle of the timing clock (F8) becomes double of the immediately preceding cycle, it is impossible to achieve synchronization on arrival of the next clock. Therefore, in case of detecting that the k-th timing clock (F8) corresponding to the packet k is yet to arrive, reading may be performed up to the tail end of the packet k and the reproduction operation may be similarly temporarily stopped as in the synchronous operation mode 1.

As described above, according to the synchronous operation mode 2, the clock signal and the reproduction of the data may be synchronized with each other, and the reproduction content can be prevented from becoming discontinuous.

Description will now be given as to the processing in the main body 1 and the processing in the external clock device (external MIDI equipment) 2 in order to effect the synchronous reproduction operation shown in the synchronous operation modes 1 and 2 mentioned above with reference to the flowcharts.

FIG. 6 is a flowchart for explaining the overall operation of the main body 1; FIG. 7, a flowchart of the MIDI monitoring timer interruption processing; FIG. 8, a flowchart of the reproduction timer interruption processing in order to realize the synchronous operation mode 1; FIG. 9, a flowchart

of a modification of the reproduction timer interruption processing illustrated in FIG. 8; FIG. 10, a flowchart of the reproduction timer interruption processing in order to realize the synchronous operation mode 2; and FIG. 11, an operation flowchart of the external MIDI equipment 2.

The main body 1 executes the synchronous reproduction process according to the present invention by the overall operation processing of the application program shown in FIG. 6, the MIDI monitoring timer interruption processing shown in FIG. 7, and the reproduction timer interruption processing illustrated in FIGS. 8 to 10. Here, both of the MIDI monitoring timer interruption processing and the reproduction timer interruption processing are activated by timer interruption generated by the MIDI monitoring timer and the reproduction timer provided in the clock generator 24 in a predetermined cycle. In the MIDI monitoring timer interruption processing, a MIDI message fed from the external MIDI equipment 2 is received and the processing according to that MIDI message is carried out. In the reproduction timer interruption processing, the processing for reproducing the object information is carried out in synchronization with the timing clock (F8).

In FIG. 6, when the operation of the application program for executing the synchronous information reproduction method according to the present invention is started in the main body 1, creation of various kinds of display windows, initialization of various kinds of

parameters, and initialization processing such as preparation for event monitoring are first carried out to start monitoring of a user event in the step S1. Here, the user event is an event which is generated in response to the operation by a user using an input device such as a mouse. For example, there are an event for designating the external synchronous mode, an event for directing the internal synchronous mode, an event for designating termination of a program, and an event for controlling a sound volume.

The program waits until any user event is generated (step S2), and executes a predetermined operation in accordance with occurrence of an event (step S3).

That is, if the generated user event is a program termination command event, the processing advances to the step S4 to carry out the termination processing such as nullification of windows drawn on the display screen, stop of the reproduction timer (= stop of the reproduction process), stop of the MIDI monitoring timer (= stop of the processing according to the MIDI input), release of various kinds of memory areas and others, thereby terminating this program.

Moreover, if the external synchronous mode designating event is inputted, the processing proceeds to the step S5 to activate the MIDI monitoring timer. As a result, the MIDI monitoring timer generates an interruption event for effecting the MIDI monitoring timer interruption processing in a predetermined cycle. Then, the processing returns to the step S2 and waits until a user event again occurs.

If other event is generated, the processing according to the event is conducted (step S6). That is, if there occurs an event such as designation of the internal synchronous mode, start of reproduction in the internal synchronous mode, command of stop and the like, setting of a sound volume, various settings of CG (selection of a background, setting of a view point and others), selection of a medium for actually performing reproduction in case of multiple kinds of reproduction mediums, and others, the processing according to the event is carried out. Then, the processing returns to the step S2 and waits for occurrence of a new user event. The above is a flow of the processing of the main routine in the main body 1.

FIG. 7 is a flowchart of the MIDI monitoring timer interruption processing. As described above, when the external synchronous mode is set, the MIDI monitoring timer is activated (step S5), and the MIDI monitoring timer interruption processing is executed by the interruption event generated by the MIDI monitoring timer in a predetermined cycle. In the MIDI monitoring timer interruption processing, a MIDI message supplied from the external MIDI equipment 2 is first fetched in the step S11. Then, the corresponding processing is carried out in accordance with a type of the fetched MIDI message (step S12).

At first, if there is no MIDI message received in the step S11, the processing proceeds to the step S18, and judgment is made as to whether a predetermined time (for

example, 300 msec) has passed after reception of the last MIDI message. This judgment is effected based on whether a timeout counter for counting the predetermined time is timed out. If there is no reception of any message within the predetermined time (if a result of judgment in the step S18 is YES), it is regarded that connection with the external MIDI device 2 is broken, and the mode is automatically changed to the internal synchronous mode. In addition, a message indicative of this change is displayed on the display unit 31 to stop the operation of the MIDI monitoring timer (step S19). Therefore, the MIDI monitoring timer interruption processing is not thereafter carried out unless the external synchronous mode is designated.

Additionally, if the predetermined time has not passed after reception of the last MIDI message, a result of judgment in the step S18 is NO, and the timeout counter is decremented (step S20). Consequently, counting by the timeout counter proceeds.

If the MIDI message is received and the MIDI message is fetched in the step S11, the processing according to the message is performed.

If the received message is a channel message (80 to EF) concerning actual performance, the processing advances to the step S17, and that message is supplied to the sound source 28 (FIG. 1). As a result, the processing according to that MIDI message is effected, and the automatic performance is hence carried out. Subsequently, the processing proceeds

to the step S14, and the timeout counter is reset. Then, judgment is made as to whether the processing is completed with respect to all of the MIDI messages fetched in the step S11. If any other message is fetched, the processing returns to the step S12, and the processing according to that message is executed. Further, if the processing with respect to all of the messages is completed, the current MIDI monitoring timer interruption processing is terminated, and the processing returns to the overall processing (FIG. 6).

If the MIDI message fetched in the step S11 is a timing clock (F8), the processing advances to the step S13. This timing clock (F8) is a variable clock, 24 pulses of which are transmitted with respect to one crotchet. Further, the transmission interval of this clock is appropriately changed in accordance with a performance tempo. For example, in case of Tempo = 100, since there are 100 crotchets per one minute, the transmission interval of F8 is  $60/(100 \times 24)$  sec = 25 msec.

In the step S13, a count value of a counter for counting a number of received clocks is incremented (+1), and a current time is substituted for a clock reception time register T\_Last. Furthermore, a difference from the previous F8 reception time is taken and a timing clock (F8) reception interval  $\Delta t$  is measured. Moreover, the processing proceeds to the step S14, and the timeout counter is reset. If there is no received MIDI message which is yet to be processed, the current MIDI monitoring timer interruption processing is

terminated.

In addition, if the MIDI message fetched in the step S11 is other system message, the processing according to the message is carried out in the step S16, and the timeout counter is then reset in the step S14. Thereafter, the processing proceeds to the step S15.

For example, if the received MIDI message is SONG POSITION POINTER (F2) for informing of a point at which music performance should be started, the SONG POSITION POINTER (F2) is transmitted to the sound source 28 in the step S16. Additionally, a reproduction start position of the object information is set, namely, the number of a packet to be reproduced is set to a position designated by the SONG POSITION POINTER (F2). This SONG POSITION POINTER (F2) is usually designated in units of one beat ( $F8 \times 6$ ).

If the received MIDI message is SONG SELECT (F3), reproduction data having an ID designated by the SONG SELECT (F3) is selected from the reproduction data stored in the external storage device 27 in the step S16, and the selected reproduction data is loaded into the RAM 23. In this connection, if the SONG SELECT (F3) is received during reproduction of a song, reproduction of that song may be forcibly terminated.

If the received MID message is START (FA), the position of the packet to be reproduced in the reproduction data selected by the SONG SELECT (F3) is reset to the top position, and the reproduction timer is activated. The



reproduction timer generates an interruption event for carrying out the reproduction process of the reproduction data in a predetermined cycle F, thereby starting the reproduction operation.

If the received MIDI message is CONTINUE (FB), the reproduction operation is restarted from a position of the packet designated by the SONG POSITION POINTER (F2) in the reproduction data selected by the SONG SELECT (F3) or a position of the packet at which reproduction is stopped by STOP (FC). That is, the reproduction timer is activated or reactivated.

If the received MID message is STOP (FC), the reproduction timer is stopped to halt the reproduction process. Meanwhile, if the STOP (FC) is received during the reproduction, the reproduction point is set in units of one beat.

If the received MID message is ACTIVE SENSING (FE), the processing of the step S16 is terminated as it is, thereby proceeding to the step S14.

Incidentally, a number of received clocks in the later-described reproduction timer interruption processing is basically reset to 0 in accordance with reception of START (FA) mentioned above. However, if the SONG POSITION POINTER (F2) is received or if reproduction is stopped by the STOP (FC), a number of received clocks is set to a number corresponding to the SONG POSITION POINTER (F2) or a number corresponding to a packet position at which reproduction is

stopped by the STOP (FC) and thereafter restarted.

As described above, in the MIDI monitoring timer interruption processing, the MIDI message is fetched in accordance with a predetermined cycle, and the processing according to the received MIDI message is performed. Furthermore, if no MIDI message is received beyond a predetermined time (for example, 300 msec), it is determined that the connection with the external MIDI equipment 2 is broken, and the processing for switching to the internal synchronous mode is carried out.

Description will now be given as to the reproduction timer interruption processing. It is to be noted that reproduction of a single set of object information will be explained hereinafter for the sake of simplicity. In case of reproducing a plurality of sets of object information, the processing such as generation of a reproduction point, reading of reproduction data, generating of a reproduction output signal and others may be carried out relative to respective sets of reproduction data in parallel.

Description will be first given on the reproduction timer interruption processing in case of performing the processing in the synchronous operation mode 1 explained with reference to FIGs. 4(d) and 5(d). FIG. 8 is an operation flowchart of the reproduction timer interruption processing in order to enable the operation in the above-mentioned synchronous operation mode 1.

As described above, if reproduction of the object

data is directed by START (FA), CONTINUE (FB) or a user event, the reproduction timer is made active, and this processing is executed in accordance with a predetermined interruption cycle F.

In this reproduction timer interruption processing, judgment is first made as to whether the current mode is the internal synchronous mode (step S21). If the current mode is the internal synchronous mode as a result of judgment, the processing advances to the step S28, and a reading position (reproduction point) Ptr of the packet data is calculated by the following expression (1). That is:

$$\text{Ptr} = \text{Ptr} + C \quad (1)$$

where C is a speed for reading the packet (reproduction speed). In this connection, since the reproduction point Ptr is actually a value including a decimal figure, the spline interpolation and the like is effected from the packet data in the vicinity of the reproduction point, thereby generating data at a corresponding point. Then, the processing proceeds to the step S29.

If the current mode is not the internal synchronous mode, the processing advances to the step S22, and judgment is made as to whether a timing clock (F8) has been newly received before the current reproduction timer interruption processing. If it is determined that the timing clock (F8) has been received as a result of the judgment, the reading packet number is shifted to the number of a next packet, and

the F8 reception interval measured in the step S13 of the MIDI monitoring timer interruption processing is used to update the reproduction speed C. Further, the reading position is reset (set to the top of the next packet), and a predicted reception time of a next timing clock (F8) is updated (step S23).

Here, the new reproduction speed C is updated based on the size of the packet (number of data) L from which reading is started, the reception interval  $\Delta t$  of F8, and the reproduction timer interruption cycle F (which depends on a type of object information and hardware). That is:

$$C = \Delta t / (F \times L) \quad (2)$$

Further, a predicted reception time  $t_{\text{next}}$  of a next timing clock (F8) is updated based on the following expression:

$$t_{\text{next}} = t_{\text{last}} + \Delta t \quad (3)$$

Then, the processing advances to the step S24 and judgment is made upon an out of synchronization. That is, a number of packets (packet number) at this moment is compared with a number of F8 received after start of reproduction to check if these numbers coincide with each other.

If it is determined that these numbers do not coincide with each other as a result of judgment, the processing advances to the step S25 because of the out of synchronism, and the current mode is changed to the internal synchronous mode. Further, a message informing of this change is displayed and the MIDI monitoring timer is stopped.

Consequently, the synchronous processing according to reception of the timing clock is not performed, but the reproduction is continued at the current reproduction speed C. Then, the processing proceeds to the step S31. On the other hand, if these numbers coincide with each other, the processing directly advances to the step S31. In case of the external synchronous mode, the timing clock (F8) transmitted from the external MIDI equipment 2 is synchronized with the reproduction timing of each packet in the above-described manner.

On the other hand, if F8 is not received in the step S22, the processing advances to the step S26, and judgment is made as to whether the current time exceeds the time  $t_{next}$  at which F8 is predicted to be received.

If it is determined that the current time exceeds the predicted time  $t_{next}$  as a result of judgment, since the reading position has reached the tail end of the packet which is currently read, the processing advances to the step S27, and reading of the packet is temporarily stopped until a next clock arrives. It is to be noted that the processing is not substantially carried out in the next step S31 in this case.

On the other hand, if the current time does not exceed the predicted time  $t_{next}$ , the processing advances to the step S28, and the expression (1) is used to calculate the reproduction point in this reproduction timing as similar to the above-described case. Then, the processing advances to the step S29.

In the step S29, judgment is made as to whether the reproduction point calculated in the step S28 exceeds a length (size) of the packet which is currently reproduced. If it does not exceed the length, the processing advances to the step S31. However, if it exceeds the length, the packet number is updated to the number of a next packet, and the reproduction point is set to a position of the top (= 0) of that packet. Then, the processing proceeds to the step S31.

As described above, after execution of the processing such as the steps S25, S30 and others, the processing advances to the step S31 where the object data is read from the reproduction point designated in each case. At this time, the reproduced data is located at a position (address) shifted rearwards from the reproduction point by an amount of the later-described offset. Subsequently, the interpolation processing is carried out with respect to the read reproduction data according to needs, and the processing for generating the reproduction output signal in this timing is performed based on this data. For example, if the object information is CG animation data, the necessary interpolation processing is applied to the read operation data, and the resulting data is transferred to the image computation unit 30. Then, updating the object is directed.

Furthermore, in the step S31, the processing time  $T_{out}$  from start of this reproduction process to actual output of the object information to the outputting section 17 is measured. Here, the processing time  $T_{out}$  to be measured may

be either a time from commanding of reading of the reproduction data till output of the reproduction data to the outputting section 17, or a time from output of the reproduction data which has been read and subjected to the interpolation processing to processing means such as the image operating section 30 till completion of the reproduction operation (from rendering till output of data to the display unit 31 in case of CG). Moreover, an average value  $T_{out}^{AV}$  of the processing time  $T_{out}$  measured with respect to the reproduction data is calculated in advance, and the offset corresponding to the average value  $T_{out}^{AV}$  is used as a correction value for the above-described reproduction point in case of reading the reproduction data in the step 31 of the next reproduction timer interruption processing.

Therefore, as to the position of the packet data which is actually read, data is read at the position which is shifted rearwards by an amount of the offset. Consequently, it is possible to absorb a gap of synchronization depending on the hardware specifications and the like for the reproduction output timing of each medium (sounds, images and others).

Incidentally, the incoming time  $t_{next}$  of the timing clock is predicted in the reproduction timer interruption processing (1) shown in FIG. 8, the processing may be carried out in accordance with whether the reading position has reached the tail end of the packet without predicting the incoming time.

FIG. 9 is a flowchart showing a modification of the

reproduction timer interruption processing (1) mentioned above.

In this case, judgment is made as to whether a new timing clock (F8) has been received in the step S41. If it is determined that the timing clock (F8) has been received as a result of judgment, the processing proceeds to the step S42. Then, as similar to the step S28 in FIG. 8, the packet is shifted to the next packet, and the incremental reproduction speed is calculated based on the reception interval of F8 and a number of data in the packet. Moreover, the reproduction point is set to a position of the top of the next packet. However, the processing for updating the predicted reception time of the next timing clock (F8) is not performed. Then, the processing advances to the step S43, and judgment is made if out of synchronism occurs. In case of no out of synchronization as a result of judgment, the processing directly proceeds to the step S50. On the other hand, in case of the out of synchronization, the processing advances to the step S44, a message informing the out of synchronization and change to the internal synchronous mode is displayed. Subsequently, the current mode is switched to the internal synchronous mode, and the MIDI monitoring timer is stopped. Thereafter, the processing proceeds to the step S50.

If the timing clock (F8) has not been received and a result of judgment in the step S41 is NO, the processing advances to the step S45, and the reproduction point Ptr at



which object information should be read in this reproduction timing is calculated based on the expression (1). Moreover, in the step S46, judgment is made as to whether the reproduction point Ptr calculated in the step S45 is a position exceeding the length (size) of the packet which is currently read. If it is determined that the reproduction point Ptr does not exceed the length of the packet as a result of judgment, the processing directly proceeds to the step S50. If the reproduction point Ptr exceeds the length of the packet, the processing advances to the step S47, and judgment is made as to whether the current operation mode is the internal synchronous mode. In case of the internal synchronous mode as a result of judgment, the processing proceeds to the step S48, and the packet number is updated to the number of a next packet, and the reproduction point is corrected to a position of the top of that packet. On the other hand, in case of no internal synchronous mode, namely, in case of the external synchronous mode, the processing proceeds to the step S49 and reading of the packet is temporarily stopped. It is to be noted that the substantial processing is not carried out in the next step S50 in this case.

If a result of judgment in either of the step S44 or S43 is NO and a result of judgment in either of the step S48 or S46 is NO, the step S50 is subsequently executed. The step S50 reads the reproduction data located at a position where the above-described correction processing has been

carried out relative to the reproduction point designated by the packet having any packet number specified in each case mentioned above, and generates the operation data based on the read reproduction data. Further, the processing for directing updating of a display object is executed. Then, as similar to the above-described case, the time  $T_{out}$  from start of the reproduction process till completion of the reproduction operation is measured, and an average value  $T_{out}^{AV}$  of the measured time duration  $T_{out}$  is recalculated. Consequently, as described above, it is possible to absorb the loss of synchronization depending on the hardware specification for the reproduction output timing of each medium. Thereafter, the current reproduction timer interruption processing is terminated. The above is the processing flow of the main body 1 in case of effecting the operation in the synchronous operation mode 1 shown in FIGs. 4 and 5.

Description will now be given as to the reproduction timer interruption processing in case of effecting the operation in the synchronous operation mode 2 shown in FIGs. 4(e) and 5(e). FIG. 10 is an operation flowchart of the reproduction timer interruption processing for carrying out the operation in the synchronous operation mode 2 mentioned above.

As similar to the synchronous operation mode 1, if the reproduction of the sequence data is designated by START (FA), CONTINUE (FB) or a user input event, the reproduction

timer is made active, and this processing is carried out in accordance with each predetermined cycle F.

Upon starting the reproduction timer interruption processing, judgment is first made as to whether a new timing clock (F8) has been received in the step S51. Here, when operating in the internal synchronous mode, the MIDI monitoring timer is not operated as described above, and the MIDI monitoring timer interruption processing (FIG. 7) is not executed. Thus, a result of judgment in the step S51 is NO. Additionally, in case of operating in the external synchronous mode, if the timing clock (F8) has not been received with this reproduction timing, a result of judgment is also NO. If the timing clock (F8) has not been received and a result of judgment in the step S51 is NO, the processing advances to the step S60, and the position Ptr for reading the packet data is calculated based on the currently set reproduction speed C by using the expression (1).

On the other hand, if the timing clock (F8) has been received, the processing for updating the reproduction speed C, i.e., the reproduction synchronization based on the reception interval of the timing clock (F8) is executed at the step S52 in accordance with the reception time. This updating processing is the processing for updating the reproduction speed C using the expression (2) and for updating the predicted reception time  $t_{next}$  of a next timing clock (F8) using the expression (3), as similar to the case of the synchronous operation mode 1 mentioned above. However,

in case of the synchronous operation mode 2, the packet length (size of the packet)  $L$  is set in accordance with the reception timing of the timing clock (F8) as follows.

(a) When the clock cycle is extended:

$L$  = an amount of remaining data of the packet which is currently reproduced

$$= \text{packet length} - \text{Ptr}$$

(b) When the clock cycle is shortened:

$L$  = an amount of remaining data of the packet which is currently reproduced + a length of a next packet

$$= \text{a length of the current packet} + \text{a length of a next packet} - \text{Ptr}$$

(c) When the clock cycle is not changed:

$$L = \text{a length of a next packet}$$

That is, as a result of comparing the reception time with the predicted reception time  $t_{\text{next}}$  of the timing clock (F8) (step S52), (a) if the reception time of F8 is behind the predicted reception time (when the cycle of F8 is extended), a number of the remaining data of the packet which is currently reproduced is determined as  $L$  (step S53). Further, (b) if the reception time of the timing clock (F8) is ahead of the predicted reception time (when the cycle of F8 is shortened), a sum of a number of remaining data of the packet which is currently reproduced and a number of data included in a next packet is determined as  $L$  (step S54).

After setting the variable  $L$  in the step S53 or S54, the processing proceeds to the step S55, and the reproduction

speed C is calculated based on the expression (2) by using the reception interval of F8 and the variable L, and the predicted reception time  $t_{next}$  in the next timing, and is updated in the step S57. Furthermore, the processing advances to the step S58, and judgment is made if out of synchronization occurs in this case. However, since the packet number is not updated at this moment, the "packet number + 1" is compared with a number of received timing clocks. If the out of synchronism is determined as a result of comparison, a message informing of this state is displayed, the current mode is changed to the internal synchronous mode, and the MIDI monitoring timer is stopped (step S59). Then, the processing advances to the step S60. Furthermore, if synchronism is established, the processing proceeds to the step S63, the packet number is updated, the reproduction point is set to a position of the top of that packet, and the processing advances to the step S64.

In the step S60, the reproduction point is calculated by using the reproduction speed C according to each case mentioned above. Then, in the step S61, judgment is made as to whether the calculated reproduction point exceeds the size of the current packet. If it does not exceed, the processing advances to the step S64. If it exceeds, the processing proceeds to the step S62, the packet number is updated to the number of a next packet, and that reproduction point (reading position) is corrected. That is, if the clock cycle is delayed, the reading position Ptr may

exceed a range of the current packet. In such a case, the length of the current packet is subtracted from Ptr, and the obtained result is corrected to a corresponding reading position in a next packet. That is, the following expression is used:

$$\text{Ptr} = \text{Ptr} - \text{a current packet length} \quad (4)$$

Then, the processing proceeds to the step S64.

In the step S64, the reproduction data is read from the reproduction point determined by the step S60, S62 or S63, and the processing for generating and outputting a reproduction output signal to the outputting section is carried out. At this time, as similar to the step S31 or S50, the time required for completing the output is measured, and a deviation from the actual reproduction timing is compensated. The above is a flow of the reproduction timer interruption processing for conducting the synchronous operation mode 2 shown in FIG. 4(e) and FIG. 5(e).

FIG. 11 is a flowchart showing the operation of the external MIDI device 2. When the power supply is turned on, as similar to the above-described main body 1, the initialization processing is first performed, and monitoring of occurrence of a user event is started (Steps S71 and S72). Here, the user event is generated in accordance with the operation of the input operator 46 (various kinds of operators such as a switch or a lever on the operation panel, or various kinds of performance operators such as a keyboard or a wheel). When any user event is produced, a type of the

user event is recognized in the step S73, and corresponding processing is carried out in accordance with a type of the user event. Then, the processing returns to the step S72 to get prepared for a next user event.

The generated user event includes a reproduction setting command such as selection of a song and reproduction data, setting of a reproduction start position, a reproduction start/stop/restart command and the like. The processing advances to the step S74, and the before-described MIDI message according to each command (SONG POSITION (F2), SONG SELECT (F3), START (FA), CONTINUE (FB), STOP (FC) and the like) is generated. Furthermore, judgment is made as to whether the current mode is set to the external synchronous mode (step S75). In case of the external synchronous mode, the corresponding MIDI message is transmitted to the main body 1, and the processing proceeds to the step S77. Moreover, if the current mode is set to the internal synchronous mode, the processing directly advances to the step S77. In the step S77, the processing in its own device according to the reproduction setting command is carried out. That is, the MIDI message according to the reproduction setting command is supplied to the sound source 48, and preparations for effecting the performance processing of the set song are made. Subsequently, the processing returns to the step S72.

If the generated user event is an external synchronous mode designation event, the processing advances

to the step S78, and ACTIVE SENSING (FE) is transmitted to the external device (main body 1). In addition, transmission of the timing clock (F8) is started. Additionally, there is also started the monitoring processing by which ACTIVE SENSING (FE) is transmitted if any MIDI message is not transmitted beyond 300 msec. Then, the processing returns to the step S72. It is to be noted that transmission of the timing clock (F8) may be started after the reproduction start/restart command is made. In such a case, the timing clocks (F8) are transmitted for a predetermined number of times before transmitting START (FA) and CONTINUE (FB).

If the generated user event is other event such as setting of a performance tempo or generation of a musical tone signal according to the operation of the performance operator, the processing advances to the step S79, and the processing according to the user event is effected. For example, if the reproduction tempo (performance tempo) is changed, the transmission interval of the timing clock (F8) is changed from this moment in time (or changed after completion of reproduction of one beat or one bar) in accordance with the set tempo. Then, the processing returns to the step S72. The above is the processing operation of the external MIDI equipment 2.

Although the synchronous information reproduction apparatus according to the present invention and the embodiment of the synchronous information reproduction apparatus have been described above in detail, the present



invention is not restricted thereto, and it is possible to make various modifications such as described below.

For example, in all the devices executing synchronous reproduction, the timing for actually effecting the reproduction operation may be shifted from the timing in which the timing clock (F8) has been received. That is, in all the devices, the timing clock (F8) reception timing corresponding to a predetermined number of clocks (a number of clocks corresponding to the time of approximately 100 msec is desirable) may be stored, and the reproduction operation with the clock immediately after receiving START (FA) being used as a reference may be started upon completion of reception of the predetermined number of timing clocks (F8) without executing the actual reproduction operation from F8 immediately after reception of START (FA) till reception of the predetermined number of F8.

Further, in the above-described embodiments, if SONG POSITION POINTER (F2) is received or if reproduction is stopped by STOP (FC), a number of received clocks in the reproduction timer interruption processing is set to a number corresponding to the SONG POSITION POINTER (F2) or a number corresponding to the packet position at which reproduction is stopped by STOP (FC), and then restarted. However, a number of received clocks may be always initialized to 0. In this case, judgment may be made if out of synchronism occurs in the reproduction timer interruption processing based on a number of clocks after starting the reproduction and a number

of packets after starting the reproduction.

Furthermore, in the above-described embodiments, when the reception cycle of the timing clock (F8) is changed, temporary stop of reproduction, abortion of reproducing the immediately preceding packet or counting a number of samples of sequence data which should be reproduced before receiving a next timing clock (F8) is carried out in order to recalculate the reproduction speed in this section. However, if the reproduction data is sound data such as WAVE data, the pitch may be disadvantageously changed or the waveform becomes discontinuous, thereby generating noises. As a countermeasure, a joint area in which the same content as that of a packet adjacent to each packet is recorded may be set in advance, and reading of a next packet may be started without changing the reproduction speed itself (maintaining the default reproduction speed) if the timing clock (F8) is received before reaching the tail end of the packet which is currently being read. Moreover, all of the remainder in the current packet (or a predetermined number of samples) may be continuously read, and they may be cross-faded to be outputted. In addition, if the timing clock (F8) is not received even after reaching the tail end of the packet which is currently being read, the joint area at the rear of the current packet may be repeatedly read and similarly cross-faded to be outputted at the time of receiving the timing clock (F8).

In addition, in the above-described embodiments,

although ACTIVE SENSING (FE) is transmitted from the external MIDI equipment 2 serving as a master, ACTIVE SENSING (FE) may be also transmitted from the main body 1 functioning as a slave so that mutual connection confirmation can be performed.

Further, in the above-described embodiments, the external MIDI equipment 2 transmits the timing clock (F8) before starting reproduction (before transmitting START (FA)). However, information concerning the transmission interval of the timing clock may be additionally transmitted to the slave (main body 1) as initialization information in advance.

Furthermore, in the above-described embodiments, as shown in FIG. 3(b), the reproduction data divided into blocks (divided into packets) according to each timing clock is used to generate the reproduction point in units of packet. However, the present invention can be readily applied to such a case where the reproduction data logically divided into packets is used as shown in FIG. 3(c). That is, in this case, the current reproduction point may be directly calculated from the top address of the reproduction data instead of effecting the processing such as updating the packet number or resetting the reproduction point (setting to the top of a next packet) in FIGs. 8 to 10.

Moreover, in spite of the fact that the clock master side (external MIDI equipment 2) transmits the timing clocks (F8) at a constant interval, the reception interval can be possibly slightly shifted for some reason. In order to cope with such a case, if the timing clock (F8) is received at a

time ahead or behind the predicted reception time by a predetermined period, that clock may be regarded to be received just at the predicted reception time and the processing may be then carried out.

In addition, in each of the above-described embodiments, the time  $T_{out}$  from start of the reproduction process till completion of the reproduction operation is measured every time in the steps S31, S50 and S64 in the reproduction timer interruption processing shown in FIGs. 8 to 10. However, this measurement and calculation of the average value  $T_{out}^{AV}$  may be carried out at predetermined intervals (for example, one time with respect to each packet).

Additionally, the processing for correcting the reproduction point in the object information on a single medium is carried out in the above-described embodiments. In case of reproducing a plurality of object information in parallel, with one object information of a medium having the longest time required for reproduction process being used as a reference, the reproduction point may be corrected in such a manner that the output timing of other object information of other medium can be matched with the output timing of the reference object information.

Further, although the operation of the MIDI monitoring timer is stopped in case of the internal synchronous mode in the above-described embodiments, the present invention does not have to be configured in this manner. That is, the MIDI monitoring timer interruption

processing is operated in advance and, in the internal synchronous mode, the timing clock (F8) is internally generated in the main body 1 at a default time interval or at a time interval corresponding to a finally calculated reproduction speed and written in the reception buffer in which the MIDI message received by the MIDI interface circuit 25 is written. In this case, the steps S21, S29 and S30 with the mark ※ in the reproduction timer interruption processing (1) shown in FIG. 8 and the steps S46 and S48 in the modification shown in FIG. 9 are no longer necessary. It is to be noted that the reproduction timer interruption processing illustrated in FIG. 10 does not have to be changed.

Furthermore, if the reproduction data is CG animation data indicative of the state of the music performance, drawing of a polygon object corresponding to a selected song may be started upon receiving the SONG SELECT (F3), and it is possible to enter the standby mode by repeatedly reading the leading data in the leading packet of the reproduction data in the same cycle as that of the reproduction timer. Moreover, when reproduction of the object data is completed to the tail end, the tail end portion of the reproduction data may be repeatedly reproduced until a command such as termination of the program or a change of the file is given. In addition, operation data for reproduction standby or termination standby may be prepared in advance, and the operation data for reproduction standby or termination standby may be repeatedly reproduced until the

reproduction is started or a command such as termination of the program is given.

Additionally, connection established between the external MIDI equipment 2 (clock master) and the main body 1 (slave) can be any kind of connection as far as MIDI messages can be transmitted. That is, any interface such as the MIDI interface employed in the embodiment, the serial interface, the USB, the IEEE 1394, or the Ethernet can be used. It is to be noted that the delay time of the transmission path must be compensated in case of the Ethernet. Further, a wireless link can be used.

Furthermore, in the above-described embodiments, although the external MIDI equipment 2 is the sequencer and the main body 1 is a PC, the present invention is not restricted thereto. In brief, any type of device can be used as far as transmission/reception of the MIDI messages (or a synchronous signal at least equivalent to the timing clock (F8)) is secured. It is possible to use various kinds of devices such as a game machine, an audio device, a mobile phone, a MIDI device like an electronic musical instrument, and a general-purpose computer like a PC as the external MIDI equipment 2.

Moreover, a plurality of slaves (main body 1) for reproducing the sequence data may be provided in accordance with types of mediums for CG generation or WAVE data reproduction. In this case, when confirming connection, ACTIVE SENSING (FE) is transmitted from the clock master to a

plurality of slaves.

In addition, in case of the IEEE 1394, the external MIDI equipment 2 serving as the clock master may broadcast FE (which can be of course used, or connection confirmation and the clock master may be additionally informed) to all the nodes when the power supply is turned on or the external synchronous mode is started.

Additionally, the program for carrying out the processing, the sequence of data and others may be supplied to the external storage devices 27 and 47 as well as the RAMs 23 and 43 through a communication network of a public telephone service (such as a telephone network or Internet).

As described above, according to the inventive synchronous information reproduction apparatus, the synchronous information reproduction method and the storage medium storing therein a synchronous reproduction program of the present invention, multimedia information of various kinds of mediums can be synchronously reproduced with the reduced processing burdens.

Further, since the internal processing delay depending on the hardware specifications and the like can be absorbed, multimedia information on different types of mediums can be assuredly synchronized.

Furthermore, since the external synchronous mode is switched to the internal synchronous mode when the out of synchronization and the like is caused due to, e.g., disconnection, the processing is not suddenly stopped.

Moreover, by informing of this switching, a user-friendly system can be provided.

In addition, selection of a file to be reproduced and the reproduction control can be executed from an external device.

111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
2184  
2185  
2186  
2187  
2188  
2189  
2190  
2191  
2192  
2193  
2194  
2195  
2196  
2197  
2198  
2199  
2200  
2201  
2202  
2203  
2204  
2205  
2206  
2207  
2208  
2209  
2210  
2211  
2212  
2213  
2214  
2215  
2216  
2217  
2218  
2219  
2220  
2221  
2222  
2223  
2224  
2225  
2226  
2227  
2228  
2229  
2230  
2231  
2232  
2233  
2234  
2235  
2236  
2237  
2238  
2239  
2240  
2241  
2242  
2243  
2244  
2245  
2246  
2247  
2248  
2249  
2250  
2251  
2252  
2253  
2254  
2255  
2256  
2257  
2258  
2259  
2260  
2261  
2262  
2263  
2264  
2265  
2266  
2267  
2268  
2269  
2270  
2271  
2272  
2273  
2274  
2275  
2276  
2277  
2278  
2279  
2280  
2281  
2282  
2283  
2284  
2285  
2286  
2287  
2288  
2289  
2290  
2291  
2292  
2293  
2294  
2295  
2296  
2297  
2298  
2299  
2300  
2301